

## AU General Risk Assessment

Brief Description of Activity:					Assessor/s:	Date:
HAND TOOLS Types of powered tools commonly used include drills, saws, sanders and bench- mounted grinders.				l bench-		
Hazard:	<u>Persons</u> at risk:	Risk factor: For each hazard, decide level of risk as if you were to do the activity without controls, see appendix B			Control measures required:	<u>Residual Risk:</u>
List what could cause harm from this activity, use appendix A to assist in identifying hazards	List who might be harmed eg staff, students, visitors				For each hazard. List the measures you will be taking to minimise the risk identified, e.g. appointing competent persons, training received, planning and try-outs, use of personal protective equipment	For each hazard now decide the residual risk after
		Severity	Likelihood	Risk		the control measures are in place
Fire	All	Very Severe	Unlikely	High	Ensure that there are no combustable materials in the vicinity if the equipment could possibly cause a spark. Store all flammable substances in appropriate CoSHH stores. Ensure that an appropriate fire risk assessment of the area has been undertaken and that everyone is aware of the evacuation procedures. Do not use heat generating equipment without a 'Hot Work' permit.	Low
Dust	User	Moderate	Possible	Medium	Operations should be carried out in very well ventilated areas. Ensure that natural ventilation is as good as possible by opening all doors and windows. If necessary, local exhaust ventilation should be provided and maintained. Operations which involve excessive generation of dust (e.g. sanding) must only be undertaken whilst wearing an appropriate dust mask which conforms to the relevant British Standard. Clear away and dust deposits when finished. Where possible, vacuum rather than sweep or brush. Wear a dust mask when cleaning up, as this operation can also generate further dust clouds.	Low
Ejected Materials and Parts	User	Severe	Unlikely	High	Ensure that equipment is correctly set up and adjusted before use. Use only the correct tooling for powered equipment. Do not use equipment for any purpose for which it has not been designed. If working on a small workpiece, it must be securely clamped. All guards fitted to, or provided with equipment, must be used. Wear appropriate protective equipment. Protective eyewear is a minimum requirement, but a face shield is preferable. Ensure that all protective equipment conforms to the correct British Standard. The abrasive wheel of a grinding machine must only be changed by a person who is fully trained in changing and dressing abrasive wheels. Fitting an incorrect wheel can lead to disintegration, and ejection of the broken bits. Isolate area is necessary and possible.	Low





Moving Parts -User Possible All equipment must be used in accordance with training and manufacturers Severe Medium Hiah instructions. Tools must only be used for the purpose for which they have Entanglement been designed. Any guards fitted to, or supplied with equipment, must be used. Power to tools must be isolated (e.g. unplugged) before any adjustments are undertaken. Always check that the operating switch is not in the 'on' position before connecting equipment to the power supply. Hair, ties, iewellerv and other clothing can become entangled in the moving parts of powered tools leading to serious injury. Ensure that there is no loose clothing etc. which could become entangled. Medium All powered tools should operate at 110 volts or less (e.g. cordless drills). Electricity User Verv Verv Low The supply from the mains socket to a 110 volt transformer must be kept as Severe Unlikelv short as possible, and not exceed 1.5 metres. Any extension leads are therefore at 110 volts and not 240 volts. All electrical equipment must be tested for safety. Equipment which has not been tested, or which has failed, must not be used. Any equipment over 2 years old should be PAT tested annually. Inspect electrical equipment before use. Look for damage to the lead, or the plug. If low voltage equipment cannot be used, then other precautions must be taken. These will include isolating transformers and residual current devices. Hidden or buried cables should be identified before any drilling commences. Do not work where water is present. Wear hearing protection if breaches the safe levels as stated in The Control Noise User Severe Unlikely Low of Noise at Work Regulations 2005. If in doubt, ask for an assessment if it has not been completed. Wear hearing protection as a precaution if the user feels more comfortable, even if the noise does not breach a threshold. Advise nearby people if noise is a hazard. Users should have been advised on the risks of noise. Vibration User Moderate Possible Medium Select power tools with the minimum level of vibration and mimimise the time Low that it is used as per the manufacturers information. Arrange health survelance for regular users. Ensure there is adequate room to complete the task and that a manual Manual User Moderate Unlikely Very Low Medium handling assessment has been completed if necessary. Repetitive activities Handling/Ergonomics should be avoided. Relevant PPE should be worn.

## AU General Risk Assessment





## AU General Risk Assessment

Situational hazards Tick		Physical / chemical hazards Tick		Health hazards	Ticl	
Assault by person		Contact with cold liquid / vapour		Disease causative agent		
Attacked by animal		Contact with cold surface		Infection		
Breathing compressed gas		Contact with hot liquid / vapour		Lack of food / water		
Cold environment		Contact with hot surface		Lack of oxygen		
Crush by load		Electric shock		Physical fatigue		
Drowning		Explosive blast		Repetitive action		
Entanglement in moving machinery		Explosive release of stored pressure		Static body posture		
High atmospheric pressure		Fire		Stress		
Hot environment		Hazardous substance		Venom poisoning		
Intimidation		Ionising radiation				
Manual handling		Laser light		Environmental hazards		
Object falling, moving or flying		Lightning strike		Litter		
Obstruction / exposed feature		Noise		Nuisance noise / vibration		
Sharp object / material		Non-ionising radiation		Physical damage		
Shot by firearm		Stroboscopic light		Waste substance released into air		
Slippery surface		Vibration		Waste substance released into soil / water		
Trap in moving machinery						
Trip hazard		Managerial / organisational hazards				
Vehicle impact / collision		Management factors				
Working at height						

## Appendix B

<b>Risk matrix</b> – use this to determine risk for each hazard i.e. 'how bad and how likely'	Likelihood of Harm					
	Remote	Very unlikely	Unlikely	Possible	Likely	
Severity of Harm						
Negligible e.g. small bruise	Very low	Very low	Very low	Low	Low	
Slight e.g. small cut, deep bruise	Very low	Very low	Low	Low	Medium	
Moderate e.g. deep cut, torn muscle	Very low	Low	Medium	Medium	High	
Severe e.g. fracture, loss of consciousness	Low	Medium	High	High	Extremely high	
Very Severe e.g. death, permanent disability	Low	Medium	High	Extremely high	Extremely high	

AUHSE-RA-26012015-v.3.1

